



ELECTRONIC IMPULSE GROUP SWITCH EGS61Z-230V FOR CENTRAL CONTROL




Function rotary switches






Standard setting ex factory.

Typical connection UT



Typical connection RT



Technical data page 16-10.

Recommended retail prices excluding VAT.

EGS61Z-230V



Impulse group switch for central control, 1+1 NO contacts not potential free 10 A/250 V AC, for one 230 V AC motor. Standby loss 0.4 watt only.

For installation. 45 mm long, 45 mm wide, **32 mm deep**.
State-of-the-art hybrid technology combines advantages of nonwearing electronic control with high capacity of special relays.
This impulse group switch serves to implement commands generated by the sensor relays or by switches and push-buttons and controls a 230 V motor for a shading element or a roller shutter.
Control, supply and switching voltage 230 V.
The same control voltage must be supplied to A1, A7 and A8 as to L.

By using bistable relays coil power loss and heating is avoided even in the on mode.
The switched consumer may not be connected to the mains before the short automatic synchronisation after installation has terminated.

A universal pushbutton connected to control input A1 controls the pulse signals for 'up, stop, down, stop'. A direction pushbutton for 'down' can be connected via the diode RTD (any polarity). Another direction pushbutton for 'up' is connected directly to A1. On the first control pulse 'down', EGS61Z switches over the control input A1 to 'direction pushbutton'. To switch the control input back to 'universal pushbutton', briefly switch off the power supply and switch back on. Additional control inputs A7 and A8 can be used for central control UP or DOWN with priority.

With priority because these control inputs cannot be overridden by other control inputs **as long as** the central control contact is closed. Up or DOWN is activated by a control signal. A further control signal (< 700 ms) at this control input interrupts this process immediately, a further control signal (> 700 ms) continues the process.

The time delay (delay time RV) is set by means of the rotary switch **RV**. If, the group impulse switch is in the UP or DOWN position the selected delay time runs (elapses); at time-out the device changes automatically to STOP. Therefore, the time delay must be chosen at least as long as the shading element or roller shutter will need to move from one limit position to the other.

With the rotary switch **WA** automatic reversal is controlled: in the setting from 0.5 to 2 sec. reversal time the automatic reversal is activated. In this case, it is only for DOWN that the direction is reversed on time-out of the time lag selected by means of the top rotary switch RV, e.g. to extend awnings or set Venetian blinds to a defined position.

AUTO 1: No automatic reversal and no local advanced automatic reversing system.
A7, A8 and direction pushbutton: Operation <1s → static process (contact closes only during operation)
Operation >1s → dynamic process (contact remains closed), stop command by new operation.
AUTO 2: Automatic reversal with 1s reversal time. Additionally the local advanced automatic reversing system for Venetian blinds with universal pushbutton at A1 is active: a double impulse activates a slow rotation in the opposite direction, which can be stopped with a further impulse.

EGS61Z-230V	Impulse group switch, 1+1 NO contacts 10 A	Art. No. 61200430	78,98 €/pc.
RTD	Direction pushbutton diode	Art. No. 60000015	4,45 €/pc.